

~~TOC~~

PCs tested with the TimeHarp260

We have unfortunately encountered compatibility problems of the TimeHarp 260 with a few desktop PCs. The problems are mostly found with the low-end PCs of large manufacturers like DELL and are caused by a wrong implementation of the Active State Power Management (ASPM) in the BIOS of these PCs. For all non-listed motherboards/computers a general rule is that TimeHarp should not be connected directly to the processor. You should search for a PCIe slots that are connected via the chipset (mostly all PCIe x1 or PCIe x4 Slots). The motherboard manual should contain info regarding whether a particular slot is connected directly or via chipset to the processor.

If your PC is not compatible please contact <http://support.picoquant.com>.

working mainboards / computer

Mainboard	Chipset	Comment
AsRock 880GXH/USB3	AMD 880G/SB710	
ASUS M2V	VIA K8T890/VT8237A	
ASUS M3A	AMD 770/SB600	
ASUS A8N-SLI	NVIDIA nForce4 SLI	
ASUS P8Z77-V Pro	Intel® Z77	
ASUS Z9PA-U8	Intel C602-A	only in Slot1 (lowest PClex8 Slot)
ASUS Z97-A	Intel Z97	
ASUS Z170-A	Intel Z170	
ASUS Z170 Pro Gaming	Intel Z170	
Gigabyte H61M-D2H	Intel H61	
Gigabyte Z68AP-D3	Intel Z68	
Gigabyte GA-Z87X-UD5H	Intel Z87	
Gigabyte GA-G33-DS3R	Intel G33/ICH9R	
MSI MS-7392	Intel P31/ICH7	
MSI P55A-GD55	Intel P55	
MSI P55-GD80	Intel P55	
MSI Z68A-GD65-G3	Intel Z68	OK after BIOS-Update to V25.8
MSI Z68A-GD65	Intel Z68	
MSI Z68A-GD80	Intel Z68	
SuperMicro X10SRA	Intel C612	works best in the 2 black PCIe x8 Slots
Computer	Chipset	Comment
HP ENVY 700-056	AMD A75 FCH	
Dell Precision T3400	Intel X38	Installed in SLOT 3 , PCIe 8x(4,1)

not-working mainboards / computer

Computer	Chipset	Comment
DELL Vostro 630		
DELL Optiplex 9010		
DELL Optiplex 9020 Model Minitower		
DELL Optiplex 7020		
DELL T7610		
HP 200-G1 (Model L5L54US#ABA)		
Lenovo ThinkServer TS140		

Copyright of this document belongs to PicoQuant GmbH. No parts of it may be reproduced, translated or transferred to third parties without written permission of PicoQuant GmbH. All information given here is reliable to our best knowledge. However, no responsibility is assumed for possible inaccuracies or omissions. Specifications and external appearances are subject to change without notice.



PicoQuant GmbH
Rudower Chaussee 29 (IGZ)
12489 Berlin
Germany

P +49-(0)30-1208820-89
F +49-(0)30-1208820-90
info@picoquant.com
www.picoquant.com